



E-Chrom Tech Co., Ltd.

TEL: +886-2-2511-1887

FAX: +886-2-2537-1870

EMAIL: service@echromtech.com

ADD: 10F-12, NO.20, Min Chuan W. Road, Taipei
104, Taiwan

WEB: www.echromtech.com

signal close to the Baseline noise.

- E. When integrating a chromatogram, setting of parameters has been intelligently automated by the **Default Integration**. When applying **Manual integration** for post-acquisition processing, all you need to do is just make three clicks on the mouse within the very same screen.
- F. When applying Quantitative analysis, you can conveniently choose from the whole range of Quantifying methods by making just one click.
- G. For reporting, you can customize the report in **Word** or **WordPad** application to be inclusive of the chromatogram the various calculated statistics and the manually input external reference information.
- H. Fully automated via **One-stop processing** with any Autosampler.
- I. Other features are **Export to Excel**, **Chromatogram complier**, **Result table complier**, **Save/ Load Template**, etc.

Specifications

Hardware Specifications

- Connect to computer by USB Port Digital Cable, connect to instrument by Signal cable
- 24-bit high precision Analog/Digital conversion device
- Input bipolar range: $\pm 1.3V$; $\pm 1.4V$
- Input resistance: $> 10M\Omega$
- Linearity: $\pm 0.005\%$ of full scale
- Acquisition speed: Programmable at 1, 2, 5, 10, 20 Hz.
Max of 60Hz is available upon request before delivery
- Integration sensitivity: $0.05\mu V \cdot s$
- Consistency: $\pm 0.005\%$
- Minimum resolution: $1\mu V$
- Accuracy more than 22 bit at 60H
- Equipped with a remote starter to be connected to analytical instrument or Autosampler to receive the Start/Run signal

Computer Requirements

- Intel Pentium 100 or better installed with Windows 95, 98, ME, NT, 2000, or XP
- CD-ROM driver for installation of software
- VGA graphics adapter (800×600 or higher resolution is recommended)
- 16M of RAM (32M or higher is better)
- 30M free space on hard disk for software installation
- Free COM/USB port for security key